## DAHUA open and set p2p Event alert

1. Open the browser and enter the camera IP address to log in server web.

💼 🞯 Wieb x +					- 0
← ♂ ▲ 不安全   192.168.1.200/#/					
REFERENCES					

2. Click" 🗿 ".Select "Network -- Platform Access -- P2P Enable -- Apply ",The status content will show online.

IP PTZ Camera	습 Live I	Network	▲   🖬 🕹   & admin   🔗   %				
IP TCP/IP	P2P ONVI	IF RTMP	🖵 Local				
👜 Port	Enable	4	1 Camera				
P PPPoE	After enabling the	function and connecting Internet, we will collect device	😵 Network				
DDNS	information is only used for remote access of the device. If you do not agree to enable the function, please cancel the selection of check box.						
🖻 Email	Status	• Online 5	≚ Event				
O UPnP	SN	8K01E3BYAJ2EF41	🖨 Storage				
SNMP		बि ३९ ग्रह	O System				
Bonjour			🗇 Maintenance Center				
<b>&amp;</b> Multicast							
Auto Registration		高外工作					
<b>@</b> QoS		TEL A STATE					
Platform Access	3	Apply Refresh Default					
Basic Services		6					

- 3. Connecting the camera with the DMSS app
  - ① Click"Add Device" to add a device.
  - ② scan the QR code of the Web Page.
  - $\bigcirc$  enter the device verification code.

- ④ Select "Wired Camera".
- (5) enter the device Password.





3

2

5



- 4. Set up message notifications and pop-ups to phone
  - ① Click" 🗿 " and Notification.
  - ② Enable and select notification type and save.





5.

- Click" o " and Remote configuration
  Click" Video Detection" and "Motion Detection"
- ③ Click Enable and set function

🛚 中国联通 穼	12:19 AM	@ 9% I
<	Device Details	<
General Config	l	
Device Sharin	9	>
Share devices w	ith other users.	
Device Entrus	ting	
Entrust devices perform alarm o	to service providers for peration services for ye	> them to ou,
Cloud Update		Latest Version >
Others		
Remote Config	guration	>
Alarm Output		
When an alarm output	event occurs, the syste t device to send alarm i	> m links to messages.
Storage Mana	ger	>
	Restart	
	Delete	

		·• · · · · · · · · · ·	
<	Notificati	on	
Device Door After enabling it, alarm types will b	only alarms of t e pushed	he subscribed	
Notification Type			Clear
Motion Detection	1		0
SMD			>
Intrusion Alarm			
Tripwire Alarm			
Scene Changing			
Cam Masking			
Object Detection	i.		>
Audio Detection			
People Alarm			>
Disk Alarm			>
Temperature No	within Thresh	olds	
_			_

11:47   1.0K	3/s 🕻 😇 💷 🖬	* © " 0	l Sall ∰ ≁
<	Motion D	etection	Save
Enable			
Advanced (	Configuration		
Arm/Disarn	n Period		>
Anti-dither			5s >
Sensitivity			70 >
Region Sett	ting		>
Record			
Delay			10s >
Alarm Outp	out		
Delay			10s >
Snapshot			